



MATERIAL FACT SHEET

193680 FFR-BS-00620-75A-SF100

General Data

Price List Text (EN)	Radio Noise Fiter for FR-A&F-00470-00620; C1 20m; C2 100m
Price List Text (DE)	Funkentst�rfilter f�r FR-A&F-00470-00620; C1 20m; C2 100m
Product Hierarchy	IAK21201
	INVERTER
	NEW EXTERNAL OPTIONS
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	B (Limited Availability from Stock)

e-shop: https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000193680

FA-Inverter: Filter

Type	RADIO NOISE FILTER
Series	FR-A800 SERIES
Series (2)	FR-F800 SERIES
Applicable Inverter	FR-A840-00470/00620
Applicable Inverter (2)	FR-F840-00470/00620
Rated Capacity (kW)	-
Rated Current (A)	75
Power Loss (W)	43,9
Leakage Current (mA)	<30
Protection Class	IP20

Product Dimensions & Weight

Width (mm)	251,5
Height (mm)	476
Depth (mm)	80
Weight (kg)	4,25

Logistic Dimensions & Gross Weight

Length (cm)	55,0
Width (cm)	31,0
Height (cm)	10,0
Gross Weight (kg)	5,000
Volume (cdm)	17,050

Stock Data

Planned Delivery Time (Days)	45
------------------------------	----

Life Cycle

Sales Start	18.12.2006
Predecessor	104755 / FFR-A540-75A-SF100

Export Data

Commodity Code	85044095
Legal Control (Dual Use List)	Not Listed
Country of Origin	Thailand (TH)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	NO
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT

Documentation & Media Data

CAD URL Indicator	X
-------------------	---