



MATERIAL FACT SHEET

193682 FFR-BS-00930-120A-SF100

General Data

Price List Text (EN)	Radio Noise Fiter for FR-A&F-00930; C1 20m; C2 100m
Price List Text (DE)	Funkentstörfilter für FR-A&F-00930; C1 20m; C2 100m
Product Hierarchy	IAK21201
	INVERTER
	NEW EXTERNAL OPTIONS
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	B (Limited Availability from Stock)

e-shop: https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000193682

FA-Inverter: Filter

Type	RADIO NOISE FILTER
Series	FR-A800 SERIES
Series (2)	FR-F800 SERIES
Applicable Inverter	FR-A840-00930
Applicable Inverter (2)	FR-F840-00930
Rated Capacity (kW)	-
Rated Current (A)	120
Power Loss (W)	44,9
Leakage Current (mA)	<30
Protection Class	IP20

Product Dimensions & Weight

Width (mm)	450
Height (mm)	636
Depth (mm)	120
Weight (kg)	10

Logistic Dimensions & Gross Weight

Length (cm)	72,0
Width (cm)	15,0
Height (cm)	52,0
Gross Weight (kg)	10,700
Volume (cdm)	56,160

Stock Data

Planned Delivery Time (Days)	45
------------------------------	----

Life Cycle

Sales Start	18.12.2006
Predecessor	151881 / FFR-A540-120A-SF100

Export Data

Commodity Code	85044095
Legal Control (Dual Use List)	Not Listed
Country of Origin	China (CN)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	NO
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT

Documentation & Media Data

CAD URL Indicator	X
-------------------	---

Product Packaging

Cardboard (g)	1199
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	554
Wood (g)	0
Glass (g)	0
Others (g)	0