



MATERIAL FACT SHEET

307223 FR-F840-00930-E2-60

General Data

Price List Text (EN)	Inverter; Rated Power: 45kW; 3x380-500V;In max: 93A;(45kW; 93A);IP00
Price List Text (DE)	Umrichter AC; Pn: 45kW; 3x380-500V;In max: 93A;(45kW; 93A);IP00
Product Hierarchy	IAK24202 INVERTER
Ext. Material Group	FR-F840 from 00770 to 01800 10 STANDARD ITEM
ABC Indicator	C (Non-Stock Material / Make-to-Order)

e-shop: https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000307223

Product Components

307163 / FR-AF840-00930-60	1 pc required
307205 / FR-CF80-01-E2-60	1 pc required

FA-Inverter: Inverter

Series	FR-F800 SERIES
Type	FR-F800-E INVERTER
Minimum Rated Voltage (V)	380
Min. Permissible Voltage (V)	323
Maximum Rated Voltage (V)	500
Max. Permissible Voltage (V)	550
Current Type	AC
Phases	3
Rated Output Current SLD (A)	93
Rated Output Current LD (A)	85
Rated Motor Capacity SLD (kW)	45
Rated Motor Capacity LD (kW)	45
Frequency Range (Hz)	0,2-590
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	PM SENSORLESS VECTOR CONTROL
Control Method (3)	SOFT-PWM/HIGH FREQUENCY PWM
Control Method (4)	V/F CONTROL
Motor Type	INDUCTION MOTOR, PM MOTOR
Integrated EMC Filter	YES
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	FR-DU08
Display Type	5 DIGITS LED (12 SEGMENT)
PLC Function	YES
Program Memory	6K
Program Memory Unit	STEPS
Integrated Digital Inputs	12
Digital Outputs (Transistor)	5
Digital Outputs (Relay)	2
Integrated Analogue Inputs	3
Integrated Analogue Outputs	2
IO Type of Terminal Block	SPRING CLAMP
Expandable	YES
USB	1+1 MINI
Ethernet Port	1
Built-In Network	BACnet/IP
Built-In Network (2)	CC-LINK IE FIELD NETWORK BASIC
Built-In Network (3)	MELSOFT/FA
Built-In Network (4)	MODBUS/TCP
Built-In Network (5)	SLMP
Built-In Network (6)	iQSS

Leakage Current (mA)	35(DELTA) / 2(STAR)
Power Loss SLD (W)	1110
Power Loss LD (W)	1020
Standby Power Consumption (W)	28
Protection Class	IP00

Product Dimensions & Weight

Width (mm)	435
Height (mm)	550
Depth (mm)	250
Weight (kg)	41

Logistic Dimensions & Gross Weight

Length (cm)	57,0
Width (cm)	60,0
Height (cm)	39,0
Gross Weight (kg)	41,000
Volume (cdm)	133,380

Stock Data

Planned Delivery Time (Days)	296
------------------------------	-----

Life Cycle

Sales Start	15.02.2017
Predecessor	156601 / FR-F740-00930-EC

Export Data

Commodity Code	85371091
Legal Control (Dual Use List)	Not Listed
Country of Origin	China (CN)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	NO
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
UKCA	COMPLIANT

Documentation & Media Data

Manual URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=bltdae25c2bd5f2ff94&q=FR-F840-00930-E2-60&doc-lang=en
Certificates URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt8050dd1408c11cc2&q=FR-F840-00930-E2-60&doc-lang=en
CAD URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt26ecc97a31a841c1&q=FR-F840-00930-E2-60&doc-lang=en
Network configuration file URL	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blte8cf990c7c524b4e&q=FR-F840-00930-E2-60&doc-lang=en

Product Packaging

Cardboard (g)	4400
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	50
Wood (g)	0
Glass (g)	0
Others (g)	0

Spare parts

Material	Description	Quantity	Unit
283484	FR-A840-00770-2-60 OR BIGGER CBL MA-CPU	1	PC

Material	Description	Quantity	Unit
283589	FR-A840-00930-2-60 CAPACITOR	4	PC
283707	FR-A840-00930-12120-2-60 COVER	1	PC
283708	FR-A840-00930-01800-2-60 CASE FAN	3	PC
283709	FR-A840-00930-01800-2-60 COVER FAN	3	PC
283710	FR-A840-00930-01800-2-60 COVER TERMINAL	1	PC
282888	FR-A840-00930-01160-2-60 PCB MA	1	PC
282906	FR-A840-00930-01800-2-60 PCB AUX	1	PC
307205	FR-CF80-01-E2-60	1	PC
282932	FR-A840/842/846-ALL TERMINAL BLOCK A80TA	1	PC
282940	FR-A840/842/CC2-ALL CASE CPU	1	PC
282941	FR-A840-77A-116A BALANCE RESISTOR	6	PC
283435	FR-A840-00930-01800-2-60 DM	3	PC
283439	FR-A840-00930-01800-2-60 THYRISTORMODULE	1	PC
283441	FR-A840-00930-01800-2-60 BREAKING IGBT	1	PC
283442	FR-A840-00930-01160-2-60 IGBT 2MBI200VB	3	PC
283450	FR-A840-00470-01800-2-60 FAN	3	PC
283462	FR-A840-00930-01800-2-60 INRUSH RES.	1	PC
283469	FR-A840-00930-2-60 DCCT	1	PC

Compatible products

Material	Description / Price List Text / Classification
70727	FR-A5 CBL 1 Cable for connecting Inverter and Programming panel; 1m Class 100100405: FA-Inverter: Cable
70728	FR-A5 CBL 2.5 Cable for connecting Inverter and Programming panel; 2,5m Class 100100405: FA-Inverter: Cable
70729	FR-A5 CBL 5 Cable for connecting Inverter and Programming panel; 5m Class 100100405: FA-Inverter: Cable
71044	FR-BAL-B-45K Input Reactor 3ph; 400V; for 45kW Class 100100406: FA-Inverter: Choke
88426	SC-FR-PC CONNECTION CABLE PC>INVERTER Programming Cable RS 232>RS485/422; 5m Class 100100405: FA-Inverter: Cable
127950	BU-UFS 110 Brake Unit 400V; Contin. Braking Current 44A; 10sec peak current 138A Class 100100407: FA-Inverter: Brake Option
157515	FR-ADP Adaptor Module for Operator Panel FR-DU07 Class 100100403: FA-Inverter: External Option
167612	FR-RJ45-HUB10 Distribution Module for RJ45; 10 way Class 100100403: FA-Inverter: External Option
167613	FR-RJ45-HUB4 Distribution Module for RJ45; 4 way Class 100100403: FA-Inverter: External Option
167614	FR-RJ45-TR Terminal Resistor Plug RJ45 Class 100100403: FA-Inverter: External Option
193682	FFR-BS-00930-120A-SF100 Radio Noise Fiter for FR-A&F-00930; C1 20m; C2 100m Class 100100404: FA-Inverter: Filter
209743	FFR-SI-93A-SS1 Sinusfilter for 200/400V Inverters; max. 93A; FT=4-16kHz; (W*H*D) 300*345*215mm Class 100100404: FA-Inverter: Filter
209758	FFR-DT-93A-SS1 du/dt Filter for 400V Inverters; max. 93A; FT=2-16kHz; (W*H*D) 190*240*100mm Class 100100404: FA-Inverter: Filter
221540	USB-CAB-5M USB 2.0 connection cabel, plug USB A to plug USB B (mini), 5m Class 100100303: FA-HMI: Cable
238355	FFR-HEL-H45K-E DC Link choke for 400V Inverter; 45kW; 0,84mH; 82A Class 100100406: FA-Inverter: Choke
254843	NF125-SV 3P 125A Circuit breaker 3pole. In = 125A; Icu = Ics = 25kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker

Material	Description / Price List Text / Classification
255079	NF250-SV 3P 175A Circuit breaker 3pole. In = 175A; Icu = Ics = 36kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
262948	A8NDPV1 Profibus DPV1 with Dsub Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
262949	A8NPRT_2P Profinet 2port Interface for FR-A/F800 with Drive Profile Class 100100402: FA-Inverter: Internal Option
262950	A8NEIP_2P EtherNet/IP 2port Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
265626	NV125-CV 3P 125A 2-440V 1.2.500MA JIEN C Earth-leakage Breaker 3pole; In=125A; 100/200/500mA; Icu/Ics=10/5kA at AC400V Class 100100906: FA-MCCB: Earth Leakage Circuit Breaker
265793	NV250-CV 3P 175A 2-440V 1.2.500MA JIEN C Earth-leakage Breaker 3pole; In=175A; 100/200/500mA; Icu/Ics=25/19kA at AC400V Class 100100906: FA-MCCB: Earth Leakage Circuit Breaker
269426	FR-A8AX 16-Bit-Digital-Input; BCD/Binary-Code; 24V DC; 5mA for FR-F/A800 Class 100100402: FA-Inverter: Internal Option
269427	FR-A8AY Digital-/Analog Output; Output load: 24V DC; 0,1A for FR-F/A800 Class 100100402: FA-Inverter: Internal Option
269428	FR-A8AR Relay output; 3 additional output relays for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269431	FR-A8NC CC-Link Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269432	FR-A8ND DeviceNet Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
270289	FR-HC2-H55K KIT Harmonic Converter 55 kW for Power Factor correction; 400V Class; KIT Class 100100403: FA-Inverter: External Option
273102	FR-A8NCE CC-Link IE Field Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
274514	FR-A8NP ProfibusDP Interface for FR-A/F800 with FR-A/F700 PPO types Class 100100402: FA-Inverter: Internal Option
274526	FR-A8TAT Adapter for control terminal of A/F700 to A/F800 Class 100100402: FA-Inverter: Internal Option
275503	FR Configurator-M+FR-Configurator2 FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series Class 100101203: FA-Software: Software Inverter
277945	FR-A8CN06 Heatsink Protusion Attachment for FR-F/A840-00930 bis 01800; for FR-A820-01870/ Class 100100403: FA-Inverter: External Option
283940	FR-A8AZ Analog Input/ output, Thermistor interface Class 100100402: FA-Inverter: Internal Option
284809	A8NECT_2P Ethercat 2port Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
290115	FR-A8NCN Control Net Interface for FR-A800 series Class 100100402: FA-Inverter: Internal Option
290116	FR-A8TR Screw Terminal Block for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
294939	FR-D-Sub9-A8NP-01 D-Sub9 Connection Adapter for FR-A8NP + Cover Class 100100402: FA-Inverter: Internal Option
296613	FR-LU08-01 Clear text LCD Parameter unit for all units of 800 Series (IP55) Class 100100403: FA-Inverter: External Option

Material	Description / Price List Text / Classification
298670	S-T65 AC100V Magnetic contactor. 30kW; 2NO + 2NC; Us = AC 100V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298671	S-T65 AC200V Magnetic contactor. 30kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298672	S-T65 AC24V Magnetic contactor. 30kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298674	S-T65 AC400V Magnetic contactor. 30kW; 2NO + 2NC; Us = AC 400V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298685	S-T100 AC200V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298686	S-T100 AC24V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298688	S-T100 AC400V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 400V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
307170	FR-A8ERS-60 Optioncard to change Ethernet board to serial communication Class 100100402: FA-Inverter: Internal Option
403133	FR-A8AVP Phase detection option board of FR-A/F800 Class 100100402: FA-Inverter: Internal Option
403134	FR-A8VPB-H Phase detection transformer box for FR-A8AVP Class 100100403: FA-Inverter: External Option
409899	FR-XC-H55K Multifunction Regeneration Conv.;400V class;55kW Class 100100403: FA-Inverter: External Option
409920	FR-XCL-H55K Reactor 55 kW for FR-XC-H55K Class 100100403: FA-Inverter: External Option
409928	FR-XCB-H55K Reactor box-type 55 kW for FR-XC-H55K-PWM Class 100100403: FA-Inverter: External Option
487882	FR-A8NCG Plug-in Option for CC-Link IE TSN Communication Function Class 100100402: FA-Inverter: Internal Option
500836	FR-XCG-H55K Standalone reactor for FR-XC regeneration converter; 400V class; 55kW Class 100100403: FA-Inverter: External Option
591579	RHF-5P 45-400-50-20-C High efficient double-stage passive harmonic filter for THDi <5%;400V;50Hz;45kW Class 100100404: FA-Inverter: Filter
591600	RHF-8P 45-400-50-20-C High efficient double-stage passive harmonic filter for THDi <8%;400V;50Hz;45kW Class 100100404: FA-Inverter: Filter